

**§ 73.258 Indicating instruments.**

(a) Each FM broadcast station shall be equipped with indicating instruments which conform with the specifications described in § 73.1215 for determining power by the indirect method; for indicating the relative amplitude of the transmission line radio frequency current, voltage, or power; and with such other instruments as are necessary for the proper adjustment, operation, and maintenance of the transmitting system.

(b) The function of each instrument shall be clearly and permanently shown in the instrument itself or on the panel immediately adjacent thereto.

(c) In the event that any one of these indicating instruments becomes defective when no substitute which conforms with the required specifications is available, the station may be operated without the defective instrument pending its repair or replacement for a period not in excess of 60 days without further authority of the FCC: *Provided that*, if the defective instrument is the transmission line meter of a station which determines the output power by the direct method, the operating power shall be determined by the indirect method in accordance with § 73.267(c) during the entire time the station is operated without the transmission line meter.

(d) If conditions beyond the control of the licensee prevent the restoration of the meter to service within the above allowed period, an informal letter request in accordance with § 73.3549 may be filed with the FCC, Attention: Audio Division, Media Bureau, in Washington, DC for such additional time as may be required to complete repairs of the defective instrument.

[41 FR 36818, Sept. 1, 1976, as amended at 48 FR 44805, Sept. 30, 1983; 50 FR 32416, Aug. 12, 1985; 63 FR 33876, June 22, 1998; 67 FR 13231, Mar. 21, 2002]

**§ 73.267 Determining operating power.**

(a) The operating power of each FM station is to be determined by either the direct or indirect method.

(b) Direct method. The direct method of power determination for an FM station uses the indications of a calibrated transmission line meter (respon-

sive to relative voltage, current, or power) located at the RF output terminals of the transmitter. This meter must be calibrated whenever there is any indication that the calibration is inaccurate or whenever any component of the metering circuit is repaired or replaced. The calibration must cover, as a minimum, the range from 90% to 105% of authorized power. The meter calibration may be checked by measuring the power at the transmitter terminals while either:

(1) Operating the transmitter into the transmitting antenna, and determining actual operating power by the indirect method described in § 73.267(c); or

(2) Operating the transmitter into a load (of substantially zero reactance and a resistance equal to the transmission line characteristic impedance) and using an electrical device (within ±5% accuracy) or temperature and coolant flow indicator (within ±4% accuracy) to determine the power.

(3) The calibration must cover, as a minimum, the range from 90% to 105% of authorized power and the meter must provide clear indications which will permit maintaining the operating power within the prescribed tolerance or the meter shall be calibrated to read directly in power units.

(c) *Indirect method.* The operating power is determined by the indirect method by applying an appropriate factor to the input power to the last radio-frequency power amplifier stage of the transmitter, using the following formula:

$$\text{Transmitter output power} = E_p \times I_p \times F$$

Where:

$E_p$  = DC input voltage of final radio stage.

$I_p$  = Total DC input current of final radio stage.

$F$  = Efficiency factor.

(1) If the above formula is not appropriate for the design of the transmitter final amplifier, use a formula specified by the transmitter manufacturer with other appropriate operating parameters.

(2) The value of the efficiency factor,  $F$ , established for the authorized transmitter output power is to be used for maintaining the operating power, even though there may be some variation in