

intentional radiators provided in § 15.209.

(ii) Access BPL systems that operate in the frequency range above 30 MHz over medium voltage power lines shall comply with the radiated emission limits provided in § 15.109(b).

(2) *Low voltage power lines.* Access BPL systems that operate over low-voltage power lines, including those that operate over low-voltage lines that are connected to the in-building wiring, shall comply with the radiated emission limits provided in § 15.109(a) and (e).

(c) *Interference Mitigation and Avoidance.* (1) Access BPL systems shall incorporate adaptive interference mitigation techniques to remotely reduce power and adjust operating frequencies, in order to avoid site-specific, local use of the same spectrum by licensed services. These techniques may include adaptive or “notch” filtering, or complete avoidance of frequencies, or bands of frequencies, locally used by licensed radio operations.

(i) For frequencies below 30 MHz, when a notch filter is used to avoid interference to a specific frequency band, the Access BPL system shall be capable of attenuating emissions within that band to a level at least 25 dB below the applicable Part 15 limits.

(ii) For frequencies above 30 MHz, when a notch filter is used to avoid interference to a specific frequency band, the Access BPL system shall be capable of attenuating emissions within that band to a level at least 10 dB below the applicable part 15 limits.

(iii) At locations where an Access BPL operator attenuates radiated emissions from its operations in accordance with the above required capabilities, we will not require that operator to take further actions to resolve complaints of harmful interference to mobile operations.

(2) Access BPL systems shall comply with applicable radiated emission limits upon power-up following a fault condition, or during a start-up operation after a shut-off procedure, by the use of a non-volatile memory, or some other method, to immediately restore previous settings with programmed notches and excluded bands, to avoid time delay caused by the need for man-

ual re-programming during which protected services may be vulnerable.

(3) Access BPL systems shall incorporate a remote-controllable shutdown feature to deactivate, from a central location, any unit found to cause harmful interference, if other interference mitigation techniques do not resolve the interference problem.

[70 FR 1374, Jan. 7, 2005, as amended at 71 FR 49379, Aug. 23, 2006; 76 FR 71908, Nov. 21, 2011]

#### § 15.613 Measurement procedures.

Compliance measurements for Access BPL shall be made in accordance with the Guidelines for Access BPL systems specified by the Commission.

#### § 15.615 General administrative requirements.

(a) *Access BPL Database.* Entities operating Access BPL systems shall supply to an industry-recognized entity, information on all existing Access BPL systems and all proposed Access BPL systems for inclusion into a publicly available data base, within 30 days prior to initiation of service. Such information shall include the following:

(1) The name of the Access BPL provider.

(2) The frequencies of the Access BPL operation.

(3) The postal zip codes served by the specific Access BPL operation.

(4) The manufacturer and type of Access BPL equipment and its associated FCC ID number, or, in the case of Access BPL equipment that has not been subject to certification in the past, the Trade Name and Model Number, as specified on the equipment label.

(5) The contact information, including both phone number and e-mail address of a person at, or associated with, the BPL operator's company, to facilitate the resolution of any interference complaint.

(6) The proposed/or actual date of Access BPL operation.

(b) The Access BPL database manager shall enter this information into the publicly accessible database within three (3) business days of receipt.

(c) No notification to the Commission is required.

(d) A licensed spectrum user experiencing harmful interference that is suspected to be caused by an Access