

(tune) in the frequency range 30 to 960 MHz and CB receivers that provide terminals for the connection of an external receiving antenna may be tested to demonstrate compliance with the provisions of §15.109 with the antenna terminals shielded and terminated with a resistive termination equal to the impedance specified for the antenna, provided these receivers also comply with the following: With the receiver antenna terminal connected to a resistive termination equal to the impedance specified or employed for the antenna, the power at the antenna terminal at any frequency within the range of measurements specified in §15.33 shall not exceed 2.0 nanowatts.

(b) CB receivers and receivers that operate (tune) in the frequency range 30 to 960 MHz that are provided only with a permanently attached antenna shall comply with the radiated emission limitations in this part, as measured with the antenna attached.

§ 15.113 Power line carrier systems.

Power line carrier systems, as defined in §15.3(t), are subject only to the following requirements:

(a) A power utility operating a power line carrier system shall submit the details of all existing systems plus any proposed new systems or changes to existing systems to an industry-operated entity as set forth in §90.63(g) of this chapter. No notification to the FCC is required.

(b) The operating parameters of a power line carrier system (particularly the frequency) shall be selected to achieve the highest practical degree of compatibility with authorized or licensed users of the radio spectrum. The signals from this operation shall be contained within the frequency band 9 kHz to 490 kHz. A power line carrier system shall operate on an unprotected, non-interference basis in accordance with §15.5 of this part. If harmful interference occurs, the electric power utility shall discontinue use or adjust its power line carrier operation, as required, to remedy the interference. Particular attention should be paid to the possibility of interference to Loran C operations at 100 kHz.

(c) Power line carrier system apparatus shall be operated with the min-

imum power possible to accomplish the desired purpose. No equipment authorization is required.

(d) The best engineering principles shall be used in the generation of radio frequency currents by power line carrier systems to guard against harmful interference to authorized radio users, particularly on the fundamental and harmonic frequencies.

(e) Power line carrier system apparatus shall conform to such engineering standards as may be promulgated by the Commission. In addition, such systems should adhere to industry approved standards designed to enhance the use of power line carrier systems.

(f) The provisions of this section apply only to systems operated by a power utility for general supervision of the power system and do not permit operation on electric lines which connect the distribution substation to the customer or house wiring. Such operation can be conducted under the other provisions of this part.

[54 FR 17714, Apr. 25, 1989; 54 FR 32339, Aug. 7, 1989]

§ 15.115 TV interface devices, including cable system terminal devices.

(a) Measurements of the radiated emissions of a TV interface device shall be conducted with the output terminal(s) of the device terminated by a resistance equal to the rated output impedance. The emanations of a TV interface device incorporating an intentional radiator shall not exceed the limits in §15.109 or subpart C of this part, whichever is higher for each frequency. Where it is possible to determine which portion of the device is contributing a particular radio frequency emission, the emissions from the TV interface device portion shall comply with the emission limits in §15.109, and the emissions from the intentional radiator shall comply with subpart C of this part.

(b) Output signal limits:

(1) At any RF output terminal, the maximum measured RMS voltage, in microvolts, corresponding to the peak envelope power of the modulated signal during maximum amplitude peaks across a resistance (R in ohms) matching the rated output impedance of the